Datesheet

lighBay light

- ▼ When you need to install or disassemble this light, you must turn off the power and have professionals work
- f V Our products comply with CIE 127: 2007; IEC 62031: 2008; IEC / PAS 62612: 2009 international standard
- ▼ All products company warranty policy statement as our website; and this document will describe the warranty period




Product: HighBay Light

150W


Product: nighbay Light	_	15044		
		Item	Parameters	Unit
	Power	Input voltage	AC90-265/277	V
		Watt	150±1%	W
		Input Current	0.72	Α
		Frequency	50/60	Hz
		Driver	Isolated constant current	
		PF	≥0.97	
		Lamp beads	196	PCS
		Fulx	21000±200	lm
	light	CCT	2800-6500	K
	light	CRI	Ra≥70	
		Chip	Philips 3030	
		Beam angle	60°, 90°, 120°	(Deg)
		Material	Aluminum+PC	
	characteri stics	Certification	CE RoHS TUV	
		Work Environment	-2040	${\mathbb C}$
		Working Hours	≥50000	Н
		Warranty	3	Years
	size	Base	Hooks, sling, stents	
		N.W	3.6	kg
		Package Size	38*38*19	cm
		G.W	5.1	Kg
Due done to and Due loons				

Product and Package:









Size:	φ328mm*H178.5m	
SIZE:	0.378mm"H178 5m	٦m

Quantity / Carton	1pcs
Carton Size	38*38*19cm
Gross Weight	5.1KG